

The Light Source

Mega-Turnbuckle



The Mega-Turnbuckle is CNC machined from aircraft aluminum and has a working load limit of 1,100 pounds.

With a Mega-Coupler on one end and a video wall adapter on the other, you can securely level video walls mounted to standing truss.

With a Mega-Coupler on both ends, you can precisely set the spacing between trusses or pipes.

The Mega-Turnbuckle itself has an adjustment range of 7" to 11". Adding various accessories increases the range. The part number includes this range. For example, the Mega-Turnbuckle with 2 Mega-Couplers has a range of 8" to 12" (MTB8TO12-MLM-2).

The Mega-Turnbuckle has a 3/4"-6 TPI Acme threaded rod with a 1-1/2" aluminum turnbuckle for adjusting the length. Internal 3/8"-16 TPI threads are at both ends of the Acme rod for attachments.

Order Codes

MTB7.5TO11.5-MLM Turnbuckle, Adjustable 7.5-11.5 in, MLM, Silver

MTB7TO11 Turnbuckle, Adjustable 7-11 in, Silver

MTB8TO12-MLM-2 Turnbuckle, Adjustable 8-12 in, MLM 2, Silver

MTB8TO12-MLM-X3V-P Turnbuckle, Adjustable 8-12 in, X3V Corner Mounting Plate, Silver

MTB8TO12-MLM-X3V-T Turnbuckle, Adjustable 8-12 in, X3V Quarter Turn Mounting Plate, Silver